















HSR® FEATURES

- ✓ Fully integrated UHF RFID system with built in antenna
- ✓ Battery powered with optional solar panel for off-grid deployments
- ✓ Communication over Bluetooth or Cellular service
- ✓ Local mesh network capabilities
- √ Additional RFID antenna port
- ✓ Water Resistant built for the elements
- ✓ OTA firmware upgrade capability
- ✓ On-site and remote diagnostic capabilities

SPECIFICATIONS

PHYSICAL SPECIFICATIONS

Dimensions	17.5" x 6.5" x 2.25"
Weight	9.2 lb.
Case Material	Poly-acetal plastic
Mounting	VESA 100mm pattern on back
	plate with m5 studs
Physical	IP67 Charging connector port
Interfaces	RP-TNC Antenna Expansion
	Port
	Power Button
	Bluetooth Button
	RGB Indicator LEDs

COMMUNICATIONS

Bluetooth	Bluetooth Spec v4.2,BLE
Cellular	Currently Supported Networks
XBee Mesh	2.4GHz meshParent / child configuration
WLAN (Future)	802.11 b/g/n

ACCESSORIES

ACCESSORIES	
Standard	 VESA 1-3" Diameter Pole
	Clamp Mount
	Charger
Optional	• 30W Solar Panel + Pole
	Mount
	Secondary Antenna + Cable
	Additional VESA 1-3"
	Diameter Pole Clamp Mount
	·

UHF RFID PERFORMANCE SPECIFICATIONS

Transmission Power	Up to 30 dBm (1W)
Internal Antenna Gain	 6.8 dBiC (Typical), 7.2 dBiC (Max) 5.1 dBiL (At center band)
Internal Antenna Polarization	Circular (RHCP)
Radiation Pattern Cross Section	Elliptical
Internal Antenna	• 40° (Azimuth)
Beamwidth	• 90° (Elevation)
Internal Antenna Operating Frequency	902-928 MHz
Air Interface Protocol	EPCglobal Gen 2 (ISO 18000-6C)
Maximum Tag Read Rate	750 Tags / Second
Consistent Direct Reading Distance	18+ feet ¹
Maximum Direct Read Distance	40 feet ¹
Consistent Width	15 feet in width at 7.5 feet
Reading	out ^{1,2}

Distances are dependent on tag used, surrounding conditions, and reader configuration

. Widths are expandable using additional units or secondary antennas

POWER

Lithium Ion Array
20800 mAh
12V DC charger (Provided) 20W Salar Band (Ontional)
30W Solar Panel (Optional)
72 hours in 'Monitoring Mode'
28 hours in 'Rapid Counting Mode'
Up to 2A input
Variable charging rates
dependent on input, optimized for solar
deployments